

Via Connect Plus FAQ

About Kramer Via Connect Plus

VIA Connect PLUS provides simultaneous wired and wireless presentation and collaboration for a variety of spaces with no need for any additional hardware. This cost-effective solution includes all the benefits of VIA Connect PRO together with an HDMI input. With any laptop or mobile device, meeting participants can display or stream full uninterrupted HD video (up to 1080p60), images and documents, or share any size file.

For additional information on this device, please visit the Kramer website: https://www.kramerav.com/ca/product/via%20connect%20plus#Tab_Overview

[What does a Wireless Presentation system do?](#)

Via gives iOS, Android, Chromebook, PC, and Mac users instant wireless connectivity with advanced presentation capabilities – no dongle needed!

[Printer-friendly version](#) [PDF version](#)

[How do I get set up?](#)

If you are using it for the first time, you will need to download the software on your device. Once that is downloaded, open it and enter the 4 digit code on the screen, then select “Share Screen”. Your device should appear on the screen.

[Printer-friendly version](#) [PDF version](#)

[Is there an app for tablets and mobile devices?](#)

For Android and Windows products, you will need to download the VIA app. For Apple devices, no app is needed. Connect to the VIA by selecting “Screen Mirroring”.

[Printer-friendly version](#) [PDF version](#)

[How many users can connect to VIA?](#)

Up to 254 users can connect, but only 4 can be displayed simultaneously.

[Printer-friendly version](#) [PDF version](#)

[What size of room is this device best for?](#)

This Via device can be used in small meetings to lecture halls with over 600 people.

[Printer-friendly version](#) [PDF version](#)

[What is the video output quality?](#)

High quality video streaming, supports full HD 1080p/60 (using the VIA app Multimedia feature)

[Printer-friendly version](#) [PDF version](#)

[How long is the warranty?](#)

3 year warranty.

[Printer-friendly version](#) [PDF version](#)

[Can you centrally manage each device?](#)

VIA site manager (one time purchase) allows you to centrally manage each device from one location. You can also program on/off times, turn certain features off, distribute custom wallpapers on mass and clear the log in code so the past user doesn't interfere with the next lecture.

[Printer-friendly version](#) [PDF version](#)

[Device Features](#)

Here are some other features:

Full HD Video streaming - Stream uninterrupted full-HD wireless video (up to 1080p60), images and documents in the room or from a remote location.

Integrated YouTube Player - Create playlists, share videos or drag and drop any YouTube clip to your VIA app for seamless video playback.

Do Not Disturb - Give the presenter complete control by disabling collaboration features.

VIA pad Compatible - Touch-and-Present USB device for laptops.

[Printer-friendly version](#) [PDF version](#)

[Device Specifications](#)

INPUTS 4 USB 3.0, 1 LAN on an RJ-45 connector, 1 HDMI

GRAPHIC OUTPUTS 1 HDMI, 1 mini DisplayPort

Note: Does not support graphic output to both the HDMI and Mini Display Port simultaneously

AUDIO OUTPUT 1 3.5mm mini jack for headphones/speakers

MAX. RESOLUTION For the HDMI Input: 1080p@60Hz

PROCESSOR 4th generation Intel® Dual core 1.4GHz

MAIN MEMORY 4GB, high speed

STORAGE 32GB, solid-state drive

LAN Gigabit LAN

AUDIO Analog or embedded HDMI, S/PDIF Realtek ALC269

POWER SUPPLY 65W power adapter (19V, 3.4A)

INPUT VOLTAGE 100V~220V AC, 50/60Hz, auto sensing

INCLUDED ACCESSORIES Power cord, Kramer HDMI Male to Female cable extender, VESA mounting bracket

PRODUCT DIMENSION 11.80cm x 11.50cm x 4.00cm (4.65" x 4.53" x 1.57") W, D, H

PRODUCT WEIGHT 0.5kg (1.1lbs) approx.

SHIPPING DIMENSION 23.20cm x 13.60cm x 10.00cm (9.13" x 5.35" x 3.94") W, D, H

SHIPPING WEIGHT 1.0kg (2.2lbs) approx.

[Printer-friendly version](#) [PDF version](#)

Source URL: <https://library.mcmaster.ca/wireless-display-evaluation/sections/connect-plus/accordion/connect-plus-faq>